



Learn more about  
this product



## Your Gateway to Efficient Connectivity

Kvaser Air Bridge Light HS (FCC) is a configuration-free wireless CAN bridge that achieves predictable latency, without sacrificing stability or range. Comprising a preconfigured pair of plug-and-play units to exchange raw CAN data, the Kvaser Air Bridge Light HS (FCC) is designed for environments or situations that make wired connection unsuitable or challenging e.g., between two moving parts that are connected by CAN.

This version (01008-6) complies with US certification while Kvaser Air Bridge Light HS (00808-3) is approved for the European Union. Both share the same functionality but have different radio transmission schemes due to regulatory differences.

-  **Warranty**  
2-Year warranty. See our general conditions and policies for details.
-  **Support**  
Free support for all products by contacting support@kvaser.com
-  **EAN**  
73-30130-01008-6

## Major Features

- IP65-rated aluminium housing, suitable for fixed outdoor installations.
- 2.4 GHz proprietary protocol.
- Internal antenna design, antenna output power max 18 dBm.
- Automatic baud rate detection (125K, 250K, 500K, 1M).
- Supports both 11-bit (CAN 2.0A) and 29-bit (CAN 2.0B active) identifiers.
- High-Speed CAN connection (compliant with ISO 11898-2), up to 1 Mbit/s.
- Plug and play, driverfree, and configuration-free.
- Power supplied through the CAN bus interface.
- Extended operating temperature range from -40 °C to +70 °C.
- Compatible with J1939, CANopen, NMEA 2000® and DeviceNet. Higher layer protocol translation handled by the user's application. For software support please see our Technical Associates products and our Software Download page ([www.kvaser.com](http://www.kvaser.com)).

## Support

Documentation, Kvaser CANlib SDK and drivers can be downloaded for free at [www.kvaser.com/downloads](http://www.kvaser.com/downloads).

Kvaser CANlib SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, Visual Basic, Python and t programming language.

Kvaser CAN hardware is built around the same common software API. Applications developed using one device type will run without modification on other device types.

## Technical Data

<b>Antenna Output Power</b>	Max 18 dBm approx.
<b>Antenna Type</b>	Internal Antenna
<b>CAN Bit Rate</b>	Autobaud at 1 Mbit/s, 500 kbit/s, 250 kbit/s and 125 kbit/s
<b>CAN Channels</b>	1
<b>CAN Transceivers</b>	TJA1051T
<b>Casing Material</b>	PC-ABS
<b>Connector</b>	DSUB 9 Plug
<b>Current Consumption</b>	Approx. 2W
<b>Dimensions</b>	30 x 151 x 17 mm
<b>Frequency Range</b>	2.405 GHz to 2.477 GHz
<b>IP Class</b>	IP65
<b>Operating Temperature Range</b>	-40 °C to +70 °C
<b>Packet Latency</b>	Approx. 4.8 ms
<b>Weight</b>	187 g (94 g per piece)
<b>Wireless Communication</b>	2.4 GHz Gaussian Frequency-Shift Keying (GFSK) with Frequency Hopping Spread Spectrum (FHSS) modulation